

Replacement Fuses for Sonamp Amplifiers

Replacement fuses for Sonamp Amplifiers are available from a variety of sources. In addition to local electronics outlets such as Radio Shack, there are on-line resources including Mouser Electronics (<http://www.mouser.com/>), Action-Electronics (www.action-electronics.com), and National Fuse (www.nationalfuse.com). Sonance does not sell replacement component parts, including fuses.

NOTE: Main AC Fuses are accessible externally from a fuse holder located on the rear chassis. Internal fuses are accessible only with the top cover plate removed.

WARNING: THERE ARE POTENTIALLY LETHAL VOLTAGES INSIDE THE AMPLIFIER. THEREFORE, REPLACING INTERNAL FUSES SHOULD ONLY BE DONE BY A QUALIFIED PROFESSIONAL SERVICE TECHNICIAN.

Sonamp 260

External Fuse	Internal Fuses
Main AC Fuse – 5 amp, 250volt, fast act 31.8mm L x 6.35mm W	F001 – 1 amp, 250volt, fast act F002 – 8 amp, 250volt, fast act F003 – 8 amp, 250volt, fast act *dimensions 31.8mm L x 6.35mm W

Sonamp 260MKII

External Fuse	Internal Fuses
Main AC Fuse – 5 amp, 250volt, fast act 31.8mm L x 6.35mm W	F001 – 500m amp, 250volt, fast act F002 – 8 amp, 250volt, fast act F003 – 8 amp, 250volt, fast act F004 – 500m amp, 250, fast act *dimensions 31.8mm L x 6.35mm W

ASAP3D SE

External Fuse	Internal Fuses
Main AC Fuse – 5 amp 250volt, fast act 20mm L x 5.2mm W	N/A

Sonamp 2120

External Fuse	Internal Fuses
Main AC Fuse – 5 amp 250 volt, fast act 31.8mm L x 6.35mm W	F001 – 1 amp, 250 volt fast act F002 - 10 amp, 250 volt fast act F003 – 10 amp, 250 volt fast act *dimensions 31.8mm L x 6.35mm W

Sonamp 2120 MKII

External Fuse Main AC Fuse – 5 amp, 250 volt fast act 31.8mm L x 6.35mm W	Internal Fuses F001 – 1 amp, 250 volt fast act F002 – 10 amp, 250 volt fast act F003 – 10 amp, 250 volt fast act F004 – 1 amp, 250 volt fast act *dimensions 31.8mm L x 6.35mm W
--	--

Sonamp 275

External Fuse Main AC Fuse – 5 amp, 250 volt fast act 31.8mm L x 6.35mm W	Internal Fuses F402 – 1 amp, 250 volt fast act F403 – 500m amp, 250 volt fast act *dimensions 20mm L x 5.2mm W F001 – 10 amp, 250 volt fast act F002 – 10 amp, 250 volt fast act *dimensions 31.8mm L x 6.35mm W
--	---

Sonamp 1230

External Fuse Main AC Fuse – 10 amp, 250 volt fast act 20mm L x 5.2mm W	Internal Fuses Power PCB F1 – 500m amp, 250 volt fast act Power PCB F2 – 1 amp, 250 volt fast act Amp PCB F1 & F2 – 5 amp, 250 volt fast act *dimensions 20mm L x 5.2mm W
--	--

Sonamp 1250

External Fuse Main AC Fuse – 8 amp 250 volt fast act 31.8mm L x 6.35mm W	Internal Fuses F213, F215 & F216 – 1 amp, 250 volt fast act F201 thru F212 – 5 amp, 250 volt fast act *dimensions 20mm L x 5.2mm W
---	--

Navigator Harbor

External Fuse Main AC Fuse – 2 amp, 250 volt fast act 31.8mm L x 6.35mm W	Internal Fuses F401 thru F406 – 2 amp, 250 volt fast act *dimensions 31.8mm L x 6.35mm W
--	---